

COMPOUND LAYOUT - ELECTRICAL
SCALE: 3/32"=1'-0"

1 / E01

TRUE NORTH



POWER SERVICE DIAGRAM
SCALE: N.T.S.

3 / E01

NOTES
1. COORDINATE NEW POWER SERVICE WITH UTILITY REPRESENTATIVE. SUBMIT CUT SHEETS OF METER BASE, SERVICE BREAKER, AND WIREWAY.
2. SEE DETAIL 3/E04 FOR CONDUIT BURIAL.
3. MOUNT NEMA 3R CSC SWITCH ON 6"X 6" WOODEN POST

PANEL – PPC

120/240 VOLTS 1 PHASE 3 WIRE 200 AMP MCB

LOAD DESCRIPTION	VA	BKR	CKT	φ A	φ B	CKT	BKR	VA	LOAD DESCRIPTION
CB#1 – GFI RECEP	180	20	1	1705		2	30	1525	CB#9 – RECT. FEED 7 SHELF 2
CB#2 – AIR COND. RECEP	1095	20	3		2620	4		1525	
	1095		5	2620		6	30	1525	CB#10 – RECT. FEED 8 SHELF 2
CB#3 – RECT. FEED 1 SHELF 1	1525	30	7		3050	8		1525	
	1525		9	1525		10			EQUIPPED SPACE
CB#4 – RECT. FEED 2 SHELF 1	1525	30	11		2245	12	20	720	CSC SWITCH AND CABINET
	1525		13	2365		14	20	840	UMTS CABINET NO.2 HEAT EXCHANGER (FUT)
CB#5 – RECT. FEED 3 SHELF 1	1525	30	15		2365	16		840	
	1525		17	2275		18	15	750	GSM CABINET NO.2 CABINET HEATER
CB#6 – RECT. FEED 4 SHELF 1	1525	30	19		2275	20		750	
	1525		21	2275		22	15	750	GSM CABINET NO.1 CABINET HEATER
CB#7 – RECT. FEED 5 SHELF 2	1525	30	23		2275	24		750	
	1525		25	2365		26	20	840	UMTS CABINET NO.1 HEAT EXCHANGER
CB#8 – RECT. FEED 6 SHELF 2	1525	30	27		2365	28		840	
	1525		29	1705		30	15	180	UMTS CABT NO. 1 RECEPT.
PHASE TOTALS:				16835	17195			TOTAL kVA: 34	

PANEL PPC NOTES:
PANELBOARD: PREMANUFACTURED MODULAR UNIT CONTAINING:
a. LOAD CENTER
b. MECHANICAL WALKING BEAM FOR TRANSFER OF POWER
c. (2) 200 AMP MAIN CIRCUIT BREAKERS

PANEL PPC CAPACITY: 48kVA; PANEL PPC CONNECTED LOAD (INCLUDING FUTURE): 34 kVA
34 kVA x 1.25 = 42.5 kVA
THE CONNECTED LOAD DOES NOT EXCEED PANEL PPC'S CAPACITY

+24VDC PANEL SCHEDULE (PART OF PERCELL 2-BAY POWER CABINET

BUS SECTION A			BUS SECTION B		
CKT	BRK (A)	LOAD DESCRIPTION	CKT	BRK (A)	LOAD DESCRIPTION
47			48		
45	250	GSM CABINET NO.3	46	250	SPARE
43			44		
41		UNUSEABLE (NOTE 2.)	42		UNUSEABLE (NOTE 2.)
39			40		
37	250	GSM CABINET NO.2	38	250	SPARE
35			36		
33		UNUSEABLE (NOTE 2.)	34		UNUSEABLE (NOTE 2.)
31			32		
29	250	GSM CABINET NO.1	30	250	NOKIA GSM CABINET #4
27			28		
25		UNUSEABLE (NOTE 2.)	26		UNUSEABLE (NOTE 2.)
23			24		
21	150	UMTS CABINET NO.1 CIRCUIT 1	22	150	UMTS CABINET #1 CIRCUIT 2
19			20		
17		SPACE	18		UNUSEABLE (NOTE 2.)
15		SPACE	16		
13		SPACE	14	150	UMTS CABINET #1 CIRCUIT 3
11		SPACE	12		
9		SPACE	10		UNUSEABLE (NOTE 2.)
7		SPACE	8		SPACE
5		SPACE	6	5	SMOKE DETECTOR
3		SPACE	4	10	LIGHTS & EMERGENCY VENT SYS
1		SPACE	2	50	VALERE 24VDD PDU NO.1 (IN BTRY BAY)
BUS		-48VDC CONVERTERS			

NOTES 1. THIS SCHEDULE REFLECTS THE BREAKER FOR DEPLOYMENT OF 4 GSM AND 2 UMTS RADIO CABINETS. SEE SINGLE-LINE DIAGRAM FOR QUANTITY OF BREAKERS TO INSTALL.
2. ONE BLANK SPACE IS REQUIRED BETWEEN BREAKERS RATED 100A AND HIGHER.

-48VDC BUS SECTION NO.1 (CENTER)

CKT	BRK (A)	LOAD DESCRIPTION
1	5	RET CCU-1
2	5	RET CCU-2 (IF REQUIRED)
3		SPACE
4		SPACE

VALERE +24VDC PDU NO.1 (IN BATTERY BAY)

FUSE (POS)	BRK (A)	LOAD DESCRIPTION
1	3	TMA PDU
2	10	E911 LMU (TRUE POSITION)
3		
4		
5		
6		
7		
8		
9		
10		

ELECTRICAL NOTES

THE ELECTRICAL CONTRACT FOR CONSTRUCTING THIS PROJECT SHALL INCLUDE PROVISION OF ALL LABOR, MATERIALS, EQUIPMENT, TOOLS, AND ADMINISTRATIVE TASKS REQUIRED TO COMPLETE AND MAKE OPERABLE THE ELECTRICAL INSTALLATION SHOWN ON THE DRAWINGS AND SPECIFIED HEREIN, BUT NOT LIMITED TO, THE FOLLOWING:

1. OBTAIN AND PAY FOR PERMITS ASSOCIATED WITH THE ELECTRICAL PORTION OF THIS CONSTRUCTION.
2. TEST, BALANCE, CLEAN, ADJUST, AND GUARANTEE ALL ELECTRICAL WORK IN THIS CONTRACT TO OPERATE SAFETY, PROPERLY AND CONTINUOUSLY.

GENERAL REQUIREMENTS

PRIOR TO SUBMITTING BID, VISIT THE SITE TO DETERMINE THE EXTENT OF WORK REQUIRED TO COMPLETE THE PROJECT AS SHOWN ON THE PLANS. IDENTIFY POSSIBLE CONFLICTS OBSERVED DURING VISIT AND SUBMIT, IN WRITING PRIOR TO SUBMITTING BID, CONDITIONS WHICH MAY PREVENT CONSTRUCTION OF ELECTRICAL WORK AS SHOWN ON THESE PLANS. NO ADDITIONAL CHARGE WILL BE ALLOWED FOR REMEDIATION OF FIELD CONDITIONS NOT IDENTIFIED THROUGH THIS PROCESS.

1. REGULATORY REQUIREMENTS

   WORK SHALL CONFORM TO THE FOLLOWING:
   a. NATIONAL ELECTRICAL CODE (N.E.C.), 2002 EDITION
   b. IBC – 2003 EDITION
   c. NFPA 101 LIFE SAFETY CODE

2. QUALITY ASSURANCE

   a. ALL WORK SHALL BE PERFORMED WITH A MINIMUM OF DISTURBANCE TO EXISTING STRUCTURES AND SURROUNDING AREAS. THE DEVICES INSTALLED SHALL BE PLUMB AND HAVING NO SCRATCHES OR DENTS. TAKE ALL MEASURES NECESSARY TO PROTECT NEW EQUIPMENT DURING THE COURSE OF CONSTRUCTION.

   b. MATERIALS SHALL BE NEW AND APPROVED FOR THE INTENDED USE. DEFECTIVE OR DAMAGED MATERIALS SHALL BE REPLACED OR REPAIRED AS ACCEPTABLE TO AT&T.

3. SUBMITTALS

   PROVIDE RED-LINED AS-BUILT DRAWINGS DOCUMENTING EXACT ROUTING OF ALL CONDUITS.

4. WARRANTY

   THE ELECTRICAL CONTRACTOR SHALL REMEDY, AT HIS OWN EXPENSE, ANY FAILURE OF THE WORK (INCLUDING EQUIPMENT) FOR A PERIOD OF ONE YEAR, TO CONFORM TO CONTRACT SPECIFICATIONS AND DRAWINGS. THIS SHALL INCLUDE ANY DEFECT OF MATERIAL OR WORKMANSHIP, AND ANY ADJUSTMENTS REQUIRED TO BE MADE FOR PROPER FUNCTIONING OF THE EQUIPMENT AND SYSTEMS.

PRODUCTS

1. RACEWAYS

   a. ALL WIRING SHALL BE INSTALLED IN CONDUIT.

   b. CONDUIT INSTALLED BELOW GRADE SHALL BE SCHEDULE 40 PVC.

   c. CONDUIT USED FOR FINAL CONNECTIONS INTO CABINETS SHALL BE LIQUIDTIGHT FLEXIBLE METAL CONDUIT.

   RACEWAY INSTALLATION

   e. THE TOTAL RADII OF BENDS IN A CONDUIT SHALL NOT EXCEED 360°.

2. CONDUCTORS

   a. SHALL BE AWG COPPER, SOLID THROUGH #10.
   b. SHALL HAVE 600 VOLT THWN/THHN INSULATION.

3. ANTI-OXIDATION COMPOUND

   SHALL BE BURNDY "PENETROX-E" OR THOMAS & BETTS KOPR-SHIELD.

4. LABELS

   SHALL BE ENGRAVED LAMACOID PLASTIC HAVING 1" HIGH LETTERS AND ADHESIVE BACKING.

ABBREVIATIONS

A	AMPERE	MCB	MAIN CIRCUIT BREAKER
AIC	ASYMMETRICAL INTERRUPT CURRENT	NEC	NATIONAL ELECTRICAL CODE
BCW	BARE COPPER WIRE	NTS	NOT TO SCALE
C	CONDUIT	PVC	POLYVINYL CHLORIDE
CGB	COAX GROUND BAR	P	POLE
GFI	GROUND FAULT INTERRUPTING	#	PHASE
G	GROUND	RMC	RIGID METAL CONDUIT
kVA	KILOVOLT-AMPERE	S/N	SOLID NEUTRAL
kW	KILOWATT	V	VOLT
LFMC	LIQUIDTIGHT FLEXIBLE METAL CONDUIT	W	WIRE

entrex
communication services, inc.
1575 Eye Street, N.W. Suite 350
WASHINGTON, D.C. 20005
PHONE: (202)408-0960
FAX: (202)408-0961

PROJECT NUMBER: 1072.031

BLACKWATER
MD1785
3445 GOLDEN HILL RD.
CHURCH CREEK, MD 21622

at&t
7150 STANDARD DRIVE
HANOVER, MD 21076

NO.	DATE	REVISIONS	BY	CHK	APPD
1	07-17-08	CONSTRUCTION	NB	CG	CG
0	07-11-08	CONSTRUCTION	NB	CG	CG
A	06-17-08	CONSTRUCTION REVIEW	TMF	CG	CG

SCALE: AS SHOWN | DRAWN: N.B. | DESIGNED: C.G.

ELECTRICAL PLANS AND NOTES

JOB NO.	DRAWING NUMBER
---	E01



NOTES:
1. ALL ITEMS SHOWN ARE NEW, PROPOSED, UNLESS NOTED OTHERWISE.

PLATFORM GROUNDING NOTES

1. ▬ INDICATES A MECHANICAL (LUG) BONDING CONNECTION
2. ALL WIRES SHOWN THIS PLAN SHALL BE GREEN-INSULATED THWN STRANDED COPPER
3. BOND METAL ENCLOSURES TO GROUND BAR WITH #2
4. ALL WIRES CONNECTED TO EQUIPMENT GROUND BAR SHALL BE #2
5. FASTEN WIRE WITH NYLON WIRE-SUPPORT STRAPS. DO NOT USE TIE WRAPS.

COMPOUND LAYOUT - GROUNDING
SCALE: 1/8"=1'-0"

1 / E02

TRUE NORTH

GROUNDING NOTES

1. ALL GROUND ELECTRODE SYSTEMS (INCLUDING TELECOMMUNICATION, RADIO, LIGHTNING PROTECTION, AND AC POWER) SHALL BE BONDED TOGETHER, AT OR BELOW GRADE, BY TWO OR MORE COPPER BONDING CONDUCTORS IN ACCORDANCE WITH THE NEC.

2. PERFORM IEEE FALL-OF-POTENTIAL RESISTANCE TO EARTH TESTING (PER IEEE 1100 AND 81) FOR GROUND ELECTRODE SYSTEMS. THE SUBCONTRACTOR SHALL FURNISH AND INSTALL SUPPLEMENTAL GROUND ELECTRODES AS NEEDED TO ACHIEVE A TEST RESULT OF 5 OHMS OR LESS.

3. PROPERLY SEQUENCE GROUNDING AND UNDERGROUND CONDUIT INSTALLATION TO PREVENT ANY LOSS OF CONTINUITY IN THE GROUNDING SYSTEM OR DAMAGE TO THE CONDUIT.

4. METAL CONDUIT AND TRAY SHALL BE GROUNDED AND MADE ELECTRICALLY CONTINUOUS WITH LISTED BONDING FITTINGS OR BY BONDING ACROSS THE DISCONTINUITY WITH #6 AWG COPPER WIRE UL APPROVED GROUNDING TYPE CONDUIT CLAMPS.

5. STRANDED GROUND WIRES SHALL HAVE GREEN 600 VOLT THWN INSULATION.

6. CONNECTIONS TO THE GROUND BUS SHALL NOT BE DOUBLED UP OR STACKED. BACK TO BACK CONNECTIONS ON OPPOSITE SIDES OF THE GROUND BUS ARE PERMITTED.

7. ALL GROUND CONDUCTORS BETWEEN EQUIPMENT/GROUND BARS AND THE GROUND RING, SHALL BE #2 AWG SOLID TINNED COPPER UNLESS OTHERWISE INDICATED.

8. ALUMINUM CONDUCTOR OR COPPER CLAD STEEL CONDUCTOR SHALL NOT BE USED FOR GROUNDING CONNECTIONS.

9. USE OF 90° BENDS IN THE PROTECTION GROUNDING CONDUCTORS SHALL BE AVOIDED WHEN 45° BENDS CAN BE ADEQUATELY SUPPORTED.

10. EXOTHERMIC WELDS SHALL BE USED FOR ALL GROUNDING CONNECTIONS BELOW GRADE.

11. ALL GROUND CONNECTIONS ABOVE GRADE SHALL BE FORMED USING HIGH PRESSURE COPPER C-TAPS.

12. COMPRESSION GROUND CONNECTIONS MAY BE REPLACED BY EXOTHERMIC WELD CONNECTIONS.

13. ICE BRIDGE BONDING CONDUCTORS SHALL BE EXOTHERMICALLY BONDED OR BOLTED TO THE BRIDGE AND THE TOWER GROUND BAR.

14. APPROVED ANTIOXIDANT COATINGS (I.E., CONDUCTIVE GEL OR PASTE) SHALL BE USED ON ALL COMPRESSION AND BOLTED GROUND CONNECTIONS.

15. ALL GROUND CONNECTIONS SHALL BE COATED WITH A CORROSION RESISTANT MATERIAL.

16. MISCELLANEOUS ELECTRICAL AND NON-ELECTRICAL METAL BOXES, FRAMES AND SUPPORTS SHALL BE BONDED TO THE GROUND RING, IN ACCORDANCE WITH THE NEC.

17. BOND ALL METALLIC OBJECTS WITHIN 6 FT OF MAIN GROUND WIRES WITH 1-#2 AWG TINNED COPPER GROUND CONDUCTOR.

18. DO NOT ROUTE GROUNDING CONDUCTORS THROUGH METALLIC OBJECTS THAT FORM A RING AROUND THE CONDUCTOR. CLIPS AND FASTENERS USED TO SECURE ANY GROUND WIRE SHALL BE NON-METALLIC TO PREVENT "CHOKE EFFECT."

entrex
communication services, inc.
1575 Eye Street, N.W. Suite 350
WASHINGTON, D.C. 20005
PHONE: (202)408-0960
FAX: (202)408-0961

PROJECT NUMBER: 1072.031

BLACKWATER
MD1785
3445 GOLDEN HILL RD.
CHURCH CREEK, MD 21622

at&t
7150 STANDARD DRIVE
HANOVER, MD 21076

NO.	DATE	REVISIONS	BY	CHK	APPD
1	07-17-08	CONSTRUCTION	NB	CG	CG
0	07-11-08	CONSTRUCTION	NB	CG	CG
A	06-17-08	CONSTRUCTION REVIEW	TMF	CG	CG

SCALE: AS SHOWN | DRAWN: N.B. | DESIGNED: C.G.

GROUNDING PLANS AND NOTES

JOB NO.	DRAWING NUMBER
--	E02



NOTE:
1. NUMBER OF GROUNDING BARS MAY VARY DEPENDING ON THE TYPE OF TOWER, ANTENNA LOCATIONS AND CONNECTION ORIENTATION. PROVIDE AS REQUIRED.
2. EXOTHERMIC WELDS ON TOWER PERMITTED ONLY WITH EXPRESS APPROVAL OF TOWER MANUFACTURER OR CONTRACTORS STRUCTURAL ENGINEER. USE LUGS PROVIDED FOR THIS PURPOSE.

ANTENNA CABLE GROUNDING - TOWER (1 / E03)
SCALE: N.T.S.



NOTES:
1. DO NOT INSTALL CABLE GROUND KIT AT A BEND. ALWAYS DIRECT GROUND KIT WIRE DOWNWARD TO GROUND BAR.
2. 1"X 2"X 1" TAPE WRAPPING SHALL BE INSTALLED OVER ALL WEATHERPROOFING CONNECTIONS. EXTEND TAPING A MINIMUM OF 6" BEYOND CONNECTION POINT ON COAXIAL CABLES. EACH WRAP SHALL OVERLAY THE PRECEDING LAYER TO ENSURE WATERTIGHT INTEGRITY.
3. WHERE GROUND KITS ARE LOCATED GREATER THAN (3) FEET FROM GROUND BAR, PROVIDE INSULATED #6 OF LENGTH REQUIRED FOR CONNECTION TO GROUND BAR.

CONNECTION OF CABLE GROUND KIT TO ANTENNA CABLE (2 / E03)
SCALE: N.T.S.



1. GROUND ROD SHALL BE DRIVEN VERTICALLY, NOT TO EXCEED 45 DEGREES FROM THE VERTICAL.

GROUND ROD DETAIL (3 / E03)
SCALE: N.T.S.



BONDING CONNECTIONS TO GROUND BARS (4 / E03)
SCALE: N.T.S.



GROUND BAR DETAILS (5 / E03)
SCALE: N.T.S.



NOTE: DO NOT INSTALL CABLE GROUND KIT AT A BEND AND ALWAYS DIRECT GROUND WIRE DOWN TO CIGBE

CONNECTION OF GROUND WIRE TO GROUND BAR (CIGBE) (6 / E03)
SCALE: N.T.S.



NOTE: INSPECTION HAND HOLE MAY BE CONCRETE OR PVC AND SHALL BE A MINIMUM OF 6" IN WIDTH/DIAMETER

GROUND ROD WITH ACCESS HANDHOLE (7 / E03)
SCALE: N.T.S.



FENCE POST BONDING DETAIL (8 / E03)
SCALE: N.T.S.

entrex
communication services, inc.
1575 Eye Street, N.W. Suite 350
WASHINGTON, D.C. 20005
PHONE: (202)408-0960
FAX: (202)408-0961

PROJECT NUMBER: 1072.031

BLACKWATER
MD1785
3445 GOLDEN HILL RD.
CHURCH CREEK, MD 21622

at&t
7150 STANDARD DRIVE
HANOVER, MD 21076

NO.	DATE	REVISIONS	BY	CHK	APPD
1	07-17-08	CONSTRUCTION	NB	CG	CG
0	07-11-08	CONSTRUCTION	NB	CG	CG
A	06-17-08	CONSTRUCTION REVIEW	TMF	CG	CG

SCALE: AS SHOWN | DRAWN: N.B. | DESIGNED: C.G.

GROUNDING DETAILS - 1

JOB NO.	DRAWING NUMBER
--	E03



NOTES:

1. MOUNT T1-TVSS UNIT ON EQUIPMENT FRAME HOUSING THE DSX UNIT. USE APPROPRIATE STAINLESS STEEL BOLTS WITH FLAT WASHERS AND A LOCK WASHER ON THE NUT SIDE. THE TVSS MAY BE LOCATED ON THE TELCO BACKBOARD. REFER TO MANUFACTURER'S INSTRUCTIONS.
2. ATTACH RING TERMINAL FROM SUPPLIED GROUND CONDUCTOR TO TVSS GROUND STUD. SECURELY FASTEN WITH SUPPLIED WASHER AND NUT. REFER TO MANUFACTURER'S INSTRUCTIONS FOR PROPER PERFORMANCE.
3. WHEN TVSS IS MOUNTED ON EQUIPMENT FRAME, BOND THE GROUND CONDUCTOR TO THE EQUIPMENT FRAME GROUND. ENSURE PROPER GROUNDING SURFACES. WHEN TVSS IS MOUNTED ON TELCO BACKBOARD, BOND THE GROUND CONDUCTOR TO THE TELCO GROUND BAR OR NEAREST GROUND BAR.

T1 SURGE SUPPRESSOR AC DATA MULTI-PORT (5/E04)
SCALE: N.T.S.



NOTES:

1. HAND DIG TRENCH TO AVOID DAMAGING EXISTING GROUND RING.
2. LEAN CONCRETE, RED-COLORED TOP, MAY BE USED IN PLACE OF COMPACTED SAND.
3. CONDUITS FROM AT&T SERVICE SWITCH AND TELCO HANDHOLE SHALL BE BURIED 30" BELOW GRADE.

DIRECT BURIED CONDUIT (3/E04)
SCALE: N.T.S.



ICE BRIDGE AT MONOPOLE BASE (1/E04)
SCALE: N.T.S.



CABLE CONNECTORS LOCATION (4/E04)
SCALE: 3/16"=1'-0"



NOTE:

1. DIAGRAM ILLUSTRATES EACH COAXIAL CABLE'S CONNECTION COMPONENTS AT ENTRY INTO CABINET.
2. IN-LINE SUPPRESSOR AND CURRENT INJECTOR ARE CONNECTED WITH MATING ASSEMBLY - NO JUMPER CABLE BETWEEN.
3. REFER TO PLAN 4/E04 FOR LOCATION OF COMPONENTS.

CABLE CONNECTIONS AT CABINET (2/E04)
SCALE: N.T.S.

entrex
communication services, inc.
1575 Eye Street, N.W. Suite 350
WASHINGTON, D.C. 20005
PHONE: (202)408-0960
FAX: (202)408-0961

PROJECT NUMBER: 1072.031

BLACKWATER
MD1785
3445 GOLDEN HILL RD.
CHURCH CREEK, MD 21622

at&t
7150 STANDARD DRIVE
HANOVER, MD 21076

NO.	DATE	REVISIONS	BY	CHK	APPD
1	07-17-08	CONSTRUCTION	NB	CG	CG
0	07-11-08	CONSTRUCTION	NB	CG	CG
A	06-17-08	CONSTRUCTION REVIEW	TMF	CG	CG

SCALE: AS SHOWN | DRAWN: N.B. | DESIGNED: C.G.

GROUNDING DETAILS - 2

JOB NO.	DRAWING NUMBER
---	E04



RET BILL OF MATERIALS

ITEM	DESCRIPTION	PART #	QTY.
1	REMOTE CONTROL UNIT (RCU) WITH DAISY CHAIN TERMINATION		2 EACH PER ANTENNA
2	RCUC-1 CONTROL CABLE ASSEMBLY BETWEEN RCU (1 M)	860-10007	1 PER ANTENNA
2A	RCUC-2 CONTROL CABLE ASSEMBLY BETWEEN RCU (2 M)	860-10008	AS REQ. BETWEEN ANTENNAS
3	RCUC CONTROL CABLE ASSEMBLY, LIGHTNING DEVICE TO RCU		
	RCU CABLE 3.3 FT. (1M)	860-10007	
	RCU CABLE 6.6 FT. (2M)	860-10008	
	RCU CABLE 16.4 FT. (5M)	860-10009	
	RCU CABLE 32.8 FT. (10M)	860-10010	1 PER SECTOR LENGTH AS REQUIRED
	RCU CABLE 82.7 FT. (25M)	860-10011	
	RCU CABLE 131.2 FT. (40M)	860-10012	
	RCU CABLE 196.9 FT. (60M)	860-10013	
	RCU CABLE 262.5 FT. (80M)	860-10014	
	RCU CABLE 328.1 FT. (100M)	860-10015	
4	CABLE GROUNDING KITS, 2FT., 6AWG FOR AISG CABLE	860-10031	3 EACH PER SECTOR
5	LIGHTNING PROTECTION DEVICE FOR RET	ANT. 11418 860-10030	1 EACH PER SECTOR
6	CONTROL CABLE ASSEMBLY, LIGHTNING DEVICE TO RCU (2 M) MINIMUM	ANT. 11439 860-10008	1 EACH PER SECTOR
7	CENTRAL CONTROL UNIT (CCU), -48VDC/100-240VAC	CEQ. 25507 860-10006	1 EACH PER SITE
8	\pt4.5;ANTENNAS: \ptz;SEE RF DATA SHEET FOR APPROVED KATHREIN ADT ANTENNAS		AS REQUIRED

NOTES:

1. EACH CENTRAL CONTROL UNIT (CCU) SECTOR CAN CONTROL UP TO 9 RET MODULES DUE TO THE VOLTAGE DROPS ALONG THE RET CONTROL CABLE SYSTEM. IT IS RECOMMENDED THAT EACH SECTOR OF ANTENNAS BE CONTROLLED INDEPENDENTLY ON LONG CABLE RUN VIA THE 3 AISG COMPATIBLE PORTS ON THE CENTRAL CONTROL UNIT.
2. SUPPORT RET CONTROL CABLE IN ACCORDANCE WITH MANUFACTURERS RECOMMENDATIONS.
3. USE 16MM (6 AWG) STRANDED TELCO RACK GROUND BAR IF EXISTING. OTHERWISE CONNECT TO MGB (INDOOR SITES).
4. ROUTE DC POWER IN WIREWAY OR 3/4" IMC TO EXISTING -48VDC PDU PANEL. PROVIDE 5 AMP PROTECTIVE DEVICE WHEN DIRECTLY SUPPLYING CCU. DO NOT INSTALL ANY SINGLE CONDUCTOR WIRE SIZE 1 AWG OR SMALLER IN CABLE RACK.
5. FOR MONOPOLE TOWER, USE ONLY ONE RCUC CONTROL CABLE PER SECTOR FROM CCU TO RCU AND DAISY CHAIN ALL THE ANTENNAS IN EACH SECTOR A, B & C.
6. INSTALLER TO USE EXTREME CAUTION WHEN MATING AISG CONNECTORS. OBSERVE THAT THE KEYED CONNECTORS AREALIGNED BEFORE MATING AND TIGHTENING THE CONNECTOR TO THE REQUIRED TORQUE.
7. USE A MINIMUM 2 METER CABLE BETWEEN THE CCU AND LIGHTNING PROTECTOR TO ACHIEVE THE REQUIRED DECOUPLING.
8. FOR LENGTHS OF CONTROL CABLES, SEE SITE SPECIFIC DRAWINGS.
9. MAX OVERALL LENGTHS OF SYSTEM PER SECTOR SHOULD NOT EXCEED 200 METERS FROM THE CCU TO THE FURTHEST RET.
10. TO FACILITATE WEATHERPROOFING OF ANTENNA CONNECTORS, THE RF COAX CABLES SHOULD BE INSTALLED AND WEATHERPROOFED PRIOR TO INSTALLING THE RET UNITS. TORQUE RET ANTENNA WITH 41MM WRENCH. MIN TORQUE 16 Nm MAX TORQUE 18Nm.
11. THE CCU IS TO BE POWERED WITH -48VDC WHENEVER POSSIBLE TO PROVIDE CONTINUOUS OPERATION IF BATTERY BACKUP ON THE DC PLANT IS AVAILABLE. THE AC POWER CONNECTION IS TO BE USED ONLY WHEN -48VDC IS NOT AVAILABLE.

(F) ~ FUTURE ANTENNA

RET CONTROL DIAGRAM (1 / E05)
SCALE: N.T.S.

entrex
communication services, inc.
1575 Eye Street, N.W. Suite 350
WASHINGTON, D.C. 20005
PHONE: (202)408-0960
FAX: (202)408-0961

PROJECT NUMBER: 1072.031

BLACKWATER
MD1785
3445 GOLDEN HILL RD.
CHURCH CREEK, MD 21622

at&t
7150 STANDARD DRIVE
HANOVER, MD 21076

NO.	DATE	REVISIONS	BY	CHK	APPD
1	07-17-08	CONSTRUCTION	NB	CG	CG
0	07-11-08	CONSTRUCTION	NB	CG	CG
A	06-17-08	CONSTRUCTION REVIEW	TMF	CG	CG

SCALE: AS SHOWN | DRAWN: N.B. | DESIGNED: C.G.

RET CONTROL DIAGRAM

JOB NO.	DRAWING NUMBER
--	E05





NOTES:

1. NOT USED
2. SEE SUPPLIER DOCUMENTATION FOR MANUFACTURER INSTALLED INTERNAL BRANCH CIRCUITS. SEE SHEET FOR PANEL DIRECTORY.
3. INSTALL ONE (1) 15A, 2-POLE CIRCUIT BREAKER IN PURCELL CABINET PANELBOARD FOR HEATER IN EACH NOKIA CABINET TO BE INSTALLED. LOCKOUT BREAKERS, CONNECT WIRE TO BREAKER, ROUTE TO BTS AND COIL 8-10 FEET OF CABLE FOR CONNECTION TO BTS CABINET BY NOKIA.
4. FOR +24V DC AND -48V DC CIRCUITS TO PURCELL RACK-MOUNTED EQUIPMENT, USE 1-2/C RHH, RHW OR THHN TYPE TC OR 2-1/C RHH, RHW OR THHN WIRE ROUTED IN EMT, FNC OR INTERNAL WIREWAY.
5. ALL CONDUITS SHALL BE GROUNDED/BONDED PER NEC REQUIREMENTS.
6. INSTALL CONDUIT AND WIRING FROM EXISTING TELCO NIU TO PURCELL CABINET TELCO BOX. INSTALL ONE (1) 66 BLOCK IN PURCELL CABINET TELCO BOX. (1) 66 BLOCK FOR ALARMS IS PROVIDED BY MANUFACTURER. TERMINATE ALARM WIRING ON BOTH SIDES OF BLOCK.
7. INSTALL ONE (1) 2AWG THWN GREEN INSULATED GROUND WIRE FOR EACH NOKIA BTS CABINET TO BE INSTALLED. CONNECT WITH A 2-HOLE LUG TO THE PLATFORM GROUND BAR AND COIL 8-10 FEET OF WIRE FOR CONNECTION TO BTS CABINET BY NOKIA.
8. INSTALL ONE (1) EACH 2AWG RHH OR THHN GREEN INSULATED GROUND WIRE FOR EQUIPMENT RACK GROUND BAR IN BATTERY BAY AND THE RET SURGE ARRESTOR GROUND. CONNECT AT BOTH ENDS WITH 2-HOLE LUGS.
9. FOR EACH REQUIRED T1 CIRCUIT FURNISH AND INSTALL CAT-5 T1 TRANSPORT CABLE WITH RJ48 LOOSE TERMINATIONS AND T1 TVSS, AC DATA MODEL NO. TJ1010B. GROUND T1 TVSS TO THE EQUIPMENT GROUND BAR.
10. INSTALL A 6 AWG THHN GREEN INSULATED GROUND WIRE IN LFMC CONDUITS USED FOR DC POWER THAT EXCEED 6 FEET IN LENGTH.
11. NOT USED
12. DC POWER CABLES SHALL BE COLOR CODED AS FOLLOWS:
    +24V SYS: POS = RED, RETURN (NEG) = GRAY
    -48V SYS: NEG = BLUE, RETURN (POS) = GRAY
13. CABLE TO NOKIA BTS SHALL BE FIRE RESISTANT HALOGEN-FREE, LOW-SMOKE RHH, COPPER COBRA COP-FLEX 2000, FLEXIBLE CLASS B STRANDED, OR APPROVED EQUAL. CLASS B OR I STRANDED MAY BE USED FOR OTHER CIRCUITS. COIL 8-10 FEET OF WIRE FOR CONNECTION TO BTS CABINET BY NOKIA. CONNECT WITH A 2-HOLE LUG AT BREAKER END, CONNECTOR AT BTS END PROVIDED BY NOKIA.
14. FOR SITES WHERE UMTS IS TO BE INSTALLED, SEE SITE-SPECIFIC DATA TABLE-THIS SHEET AND DETAIL 1/E07

FURNISHED BY OTHERS

SITE SPECIFIC DATA	
(NEW) DESCRIPTION	QTY
NOKIA GSM CABINETS	2
250A, 24V DC BREAKER(S) FOR GSM BTS	2
RECTIFIERS TO BE ADDED	6
CONVERTERS, 24V/48V DC	2
T1 LINES FOR GSM	2
T1 LINES FOR UMTS	2
LUCENT UMTS CABINET	1
150A, 24V DC BREAKER FOR UMTS BTS	3

LEGEND	
(E) = EXISTING	TBD = TO BE DETERMINED
(N) = NEW	(F) = FUTURE
EXISTING CONNECTIONS / EQUIP.	
NEW CONNECTIONS / EQUIP.	
FUTURE CONNECTIONS / EQUIP.	
EXISTING GROUNDING	
NEW GROUNDING	
EXISTING CONNECTIONS, CABLE AND EQUIPMENT TO BE REMOVED	X

SINGLE-LINE DIAGRAM FOR OUTDOOR NOKIA GSM CABINETS W/ PURCELL POWER CABINET

GSM SINGLE-LINE DIAGRAM
SCALE: N.T.S.
1 / E06

BECHTEL DETAIL NO.312PA-BWA

entrex
communication services, inc.
1575 Eye Street, N.W. Suite 350
WASHINGTON, D.C. 20005
PHONE: (202)408-0960
FAX: (202)408-0961

PROJECT NUMBER: 1072.031

BLACKWATER
MD1785
3445 GOLDEN HILL RD.
CHURCH CREEK, MD 21622

at&t
7150 STANDARD DRIVE
HANOVER, MD 21076

NO.	DATE	REVISIONS	BY	CHK	APPD
1	07-17-08	CONSTRUCTION	NB	CG	CG
0	07-11-08	CONSTRUCTION	NB	CG	CG
A	06-17-08	CONSTRUCTION REVIEW	TMF	CG	CG

SCALE: AS SHOWN | DRAWN: C.G. | DESIGNED: N.B.

GSM SINGLE-LINE DIAGRAM

JOB NO.	DRAWING NUMBER
--	E06



NOTES:

1. CABLE TO BE USED IS COBRA COP-FLEX 2000, FLEXIBLE CLASS I, OR APPROVED EQUAL. (BTS TERMINAL ACCEPTS MAX. CONDUCTOR SIZE OF 1/0 AWG, CLASS 1).
2. MAXIMUM TOTAL FEEDER LENGTH OF UP TO 35 FT. (CABLE LENGTHS ARE BASED ON 1.0 VOLT DROP MAXIMUM BETWEEN DC POWER PLANT AND BTS CABINET). CONDUITS SHALL BE INSTALLED TO BOTTOM REAR OF CABINET. FOR DISTANCES BETWEEN DC POWER PLANT & UMTS EQUIPMENT EXCEEDING 35 FT., CONTACT ENGINEERING FOR RESOLUTION.
3. PROVIDE AND INSTALL (1) 20A 2P BREAKER AND (1) 15A 1P BREAKER FOR LUCENT UMTS CABINET. FURNISH AND INSTALL CIRCUIT PROTECTION AND WIRING AS SHOWN. BREAKER SHALL BE COMPATIBLE WITH AND HAVE ISC RATING TO MATCH EXISTING PANELBOARD.
4. ALL CONDUITS SHALL BE GROUNDED/BONDED, PER NEC REQUIREMENTS.
5. FOR EACH REQUIRED T1 CIRCUIT, FURNISH AND INSTALL CAT-5 T1 TRANSPORT CABLE WITH RJ48 LOOSE TERMINATIONS AND T1 TVSS, AC DATA MODEL NO. TJ1010B. GROUND T1 TVSS TO THE EQUIPMENT GROUND BAR, REFER TO DETAIL 151.
6. CABLES, CONDUIT AND GND FUTURE UMTS. SUBCONTRACTOR SHALL INSTALL SUFFICIENT LENGTHS OF LFMC INCLUDING ALL CONDUIT FITTINGS (NUTS, REDUCING BUSHINGS, ELBOWS, COUPLINGS, ECT.) NECESSARY FOR CONNECTION FROM IMC CONDUIT TO UMTS CABINET. CUT, COIL AND TAPE 5' PIGTAIL FOR FUTURE CONTINUATION & TERMINATION BY OTHERS. SEAL END OF CONDUIT. ENSURE BREAKER IS OFF AND PROPERLY TAGGED. CAP OR TAPE CUT END AND ENSURE PROPER PHYSICAL PROTECTION OF COILED WIRE.
7. GROUND WIRES SHALL BE TERMINATED AT DIAGONALLY OPPOSITE CORNERS OF THE BTS CABINET. COIL 5-FOOT FOR TERMINATIONS BY OEM.
8. OVERHEAD CONDUIT ROUTING IS PERMISSIBLE ON EXISTING OR NEW, SUBCONTRACTOR PROVIDED, SUPPORTS WITH ADEQUATE SPACING AND IN COMPLIANCE WITH THE NEC INSTALLATION REQUIREMENTS ARE MAINTAINED.
9. REFER TO DETAILS 125 AND 140 FOR CONDUIT INSTALLATION WHERE TRANSITION TO UNDERGROUND IS REQUIRED, UNDERGROUND OR OVERHEAD ROUTING TO BE DETERMINED BY SITE CONDITIONS.
10. LUCENT TO ATTACH THE LUGS FOR THE DC CONNECTION TO NODE B CABINET. LUGS PART NO. YAV25LNT516FX. BECHTEL TO PROVIDE 6 LUGS TO CONTRACTOR TO BE LEFT ON SITE FOR TERMINATION OF DC CONDUCTORS.
11. INSTALL A 6 AWG THHN GREEN INSULATED GROUND WIRE IN LFMC CONDUITS USED FOR DC POWER THAT EXCEED 6 FEET IN LENGTH.
12. TWO GROUND CONNECTION POINTS ARE LOCATED AT THE REAR OF THE NODE B CABINET

LEGEND	
(E) = EXISTING	TBD = TO BE DETERMINED
(N) = NEW	(F) = FUTURE
EXISTING CONNECTIONS / EQUIP.	
NEW CONNECTIONS / EQUIP.	
FUTURE CONNECTIONS / EQUIP.	
EXISTING GROUNDING	
NEW GROUNDING	
EXISTING CONNECTIONS, CABLE AND EQUIPMENT TO BE REMOVED	X

24 VDC OUTDOOR LUCENT UMTS MACROCELL SINGLE-LINE DIAGRAM

UMTS SINGLE-LINE DIAGRAM
SCALE: N.T.S.

1
E07

BECHTEL DETAIL NO.3210-DC

entrex
communication services, inc.
1575 Eye Street, N.W. Suite 350
WASHINGTON, D.C. 20005
PHONE: (202)408-0960
FAX: (202)408-0961

PROJECT NUMBER: 1072.031

BLACKWATER
MD1785
3445 GOLDEN HILL RD.
CHURCH CREEK, MD 21622

at&t
7150 STANDARD DRIVE
HANOVER, MD 21076

NO.	DATE	REVISIONS	BY	CHK	APPD
1	07-17-08	CONSTRUCTION	NB	CG	CG
0	07-11-08	CONSTRUCTION	NB	CG	CG
A	06-17-08	CONSTRUCTION REVIEW	TMF	CG	CG

SCALE: AS SHOWN | DRAWN: N.B. | DESIGNED: C.G.

UMTS SINGLE-LINE DIAGRAM

JOB NO.	DRAWING NUMBER
--	E07



NOTES:

1. ⊙ AND ⊙⊙⊙ REPRESENT A GROUNDING TERMINAL WITH A LISTED GREEN SCREW THAT ACHIEVES CONTINUOUS METALLIC CONTACT WITH THE METAL ENCLOSURE.
2. NEUTRAL WIRES SHALL BE INSULATED AND MARKED WITH WHITE TAPE.
3. DRIVE 8' LONG GROUND RODS COMPLETELY BELOW GRADE.
4. ROUTE BARE #2 WIRE FROM SERVICE SWITCH TO BELOW GRADE IN PVC.

SERVICE GROUNDING DETAIL (2/E08)
SCALE: N.T.S.



NOTES:

1. SUBCONTRACTOR SHALL PROVIDE 200AMP, SINGLE PHASE, 120/240 VAC, 60HZ SERVICE FOR SITE.

2. SUBCONTRACTOR SHALL COORDINATE WITH UTILITY COMPANY BEFORE THE START OF CONSTRUCTION. POWER AND TELEPHONE CONDUIT SHALL BE PROVIDED AND INSTALLED PER UTILITY REQUIREMENTS.

3. SUBCONTRACTOR SHALL PROVIDE ELECTRICAL SERVICE EQUIPMENT WITH FAULT CURRENT RATINGS GREATER THAN THE AVAILABLE FAULT CURRENT FROM THE POWER UTILITY.

4. REFER TO DIAGRAM 2/E08 FOR SERVICE GROUNDING REQUIRED PER N.E.C.

5. FOR COMPLETE INTERNAL WIRING AND ARRANGEMENT REFER TO DRAWINGS PROVIDED BY PURCELL AND DRAWINGS 1/E06 AND 1/E07.

POWER DIAGRAM (1/E08)
SCALE: N.T.S.

entrex
communication services, inc.
1575 Eye Street, N.W. Suite 350
WASHINGTON, D.C. 20005
PHONE: (202)408-0960
FAX: (202)408-0961

PROJECT NUMBER: 1072.031

BLACKWATER
MD1785
3445 GOLDEN HILL RD.
CHURCH CREEK, MD 21622

at&t
7150 STANDARD DRIVE
HANOVER, MD 21076

NO.	DATE	REVISIONS	BY	CHK	APPD
1	07-17-08	CONSTRUCTION	NB	CG	CG
0	07-11-08	CONSTRUCTION	NB	CG	CG
A	06-17-08	CONSTRUCTION REVIEW	TMF	CG	CG

SCALE: AS SHOWN | DRAWN: N.B. | DESIGNED: C.G.

POWER DIAGRAM

JOB NO.	DRAWING NUMBER
--	E08



DIPLEXER MOUNTING SYSTEM (1 / E09)
SCALE: NOT TO SCALE



DIPLEXER MOUNT TO KINDORF FRAME (2 / E09)
SCALE: NOT TO SCALE



DIPLEXERS GROUNDING DETAIL (3 / E09)
SCALE: NOT TO SCALE

entrex
communication services, inc.
1575 Eye Street, N.W. Suite 350
WASHINGTON, D.C. 20005
PHONE: (202)408-0960
FAX: (202)408-0961

PROJECT NUMBER: 1072.031

BLACKWATER
MD1785
3445 GOLDEN HILL RD.
CHURCH CREEK, MD 21622

at&t
7150 STANDARD DRIVE
HANOVER, MD 21075

NO.	DATE	REVISIONS	BY	CHK	APPD
1	07-17-08	CONSTRUCTION	NB	CG	CG
0	07-11-08	CONSTRUCTION	NB	CG	CG
A	06-17-08	CONSTRUCTION REVIEW	TMF	CG	CG

SCALE: AS SHOWN | DRAWN: N.B. | DESIGNED: C.G.

DIPLEXER DETAILS

JOB NO.	DRAWING NUMBER
--	E09

Exhibit 10

FCC Environmental Assessment Checklist

The Environmental Navigators ®

FCC ENVIRONMENTAL ASSESSMENT

Applicant: _____FCC File No.: _____

The Spectrum and Competition Policy Division, Wireless Telecommunications Bureau sends "deficiency letters" to individual licensees and applicants, including tower owners, who have submitted environmental assessments (EAs) with applications (*i.e.*, a filed FCC Form 601 or FCC Form 854) when the EA submitted is insufficient or lacks necessary documentation.

The following checklist is now used by the staff as an attachment to each deficiency letter to inform the licensee, applicant, or tower owner (collectively, "Applicant") concerning compliance with 47 C.F.R. § 1.1307 of the Commission's rules. In addition to compiling this information, Applicants are required to comply with all of the Commission's environmental rules, including 47 C.F.R. § 1.1311 (i.e., "environmental information to be included in the environmental assessment (EA)"), to determine whether a proposed facility may have significant effect on the environment.

Pursuant to 47 C.F.R. § 1.1307, this EA provides insufficient information regarding the proposed facility's compliance with the following NEPA requirements:

_____ **(a)(1) will be located in an officially designated wilderness area**

Applicant provided insufficient information for the Commission's staff to determine whether the proposed facility satisfies § 1.1307(a)(1).

If the proposed facility would not be located in an officially designated wilderness area, provide an explanation of how the applicant determined that the proposed facility would not be located in an officially designated wilderness area. Applicant should cite specifically to the sections of the relevant databases, maps, references, or information from the relevant government agencies (*e.g.*, Department of the Interior).

If the proposed facility would be located in an officially designated wilderness area, provide copies of all approvals, permits, or grants from the relevant government agencies approving the proposed antenna structure (e.g. Department of the Interior).

_____ **(a)(2) will be located in an officially designated wildlife preserve**

Applicant provided insufficient information for the Commission's staff to determine whether the proposed facility satisfies § 1.1307(a)(2).

If the proposed facility would not be located in an officially designated wildlife preserve, provide an explanation of how the applicant determined that the proposed facility would not be located in an officially designated wildlife preserve. Applicant should cite specifically to the sections of the relevant databases, maps, references, or information from the relevant government agencies (e.g. Department of the Interior).

If the proposed facility would be located in an officially designated wildlife preserve, provide copies of all approvals, permits, or grants from the relevant government agencies approving the proposed antenna structure (e.g. Department of the Interior).

_____ **(a)(3) may affect listed threatened or endangered species or designated critical habitats; or is likely to jeopardize the continued existence of any proposed endangered or threatened species or likely to result in the destruction or adverse modification of proposed critical habitats**

Applicant provided insufficient information for the Commission's staff to determine whether the proposed facility satisfies § 1.1307(a)(3).[1]

_____ **If no listed[2] or proposed[3] threatened or endangered species or designated or proposed critical habitats[4] are present in the county or counties where the "action area"[5] is located:** Explain the basis for the applicant's determination that there are no listed or proposed threatened or endangered species or designated or proposed critical habitats within the county (or counties) of the project's action area and that there would be no effect on listed or proposed threatened or endangered species or designated or proposed critical habitats within the county (or counties) of the project's action area. Provide the materials (with citations) that formed the basis for this determination (*e.g.*, maps or lists from relevant U.S. Department of the Interior, Fish and Wildlife Service (FWS) databases). If the applicant received a letter from FWS indicating that there would be no effect, provide a copy of the FWS letter so indicating.

_____ **If listed or proposed threatened or endangered species or designated or proposed critical habitats *are present* in the county or counties where the "action area" is located and would not be affected by the proposed antenna structure:** Explain how the applicant determined that there would be no effect on listed or proposed threatened or endangered species or designated or proposed critical habitats within the county (or counties) of the project's action area. Provide the materials (with citations) that formed the basis for this determination (*e.g.*, maps or lists from relevant U.S. Department of the Interior, Fish and Wildlife Service (FWS) databases).

If the applicant received a letter from FWS indicating that there would be no effect, provide a copy of the FWS letter so indicating.

---

[1] Applicants who need to consult with the United States Fish & Wildlife Service regarding these matters should be aware that they are consulting with that agency pursuant to Section 7 of the Endangered Species Act. Furthermore, the applicant is pursuing such consultation as a "designated non-Federal entity." Additional, important information about this process may be found at: http://endangered.fws.gov/consultations/sec7_faq.html.

[2] "Listed species" are defined as any species of fish, wildlife or plant which has been determined to be endangered or threatened under section 4 of the Endangered Species Act.

[3] "Proposed species" are defined as any species of fish, wildlife or plant that has been proposed in the Federal Register to be listed under section 4 of the Act.

[4] "Critical habitat" is defined in Section 3 of the Endangered Species Act.

[5] U.S. Fish & Wildlife Service defines an action area as "all areas to be affected, directly or indirectly, by the federal action and not merely the immediate area involved in the action." See 50 C.F.R. §402.02(d). For example, an action area would include the site of the proposed antenna structure, its immediate vicinity, and any roads to be constructed to the tower site.

If the applicant did not receive a letter from FWS indicating that there would be no effect, provide a copy of any informal biological assessment prepared by a biologist supporting the applicant's "no effect" determination. Provide the name(s) and qualifications of the biologist(s) who prepared the biological assessment along with any FWS staff who may be familiar with its contents.[6]

_____ **If the proposed antenna structure may affect, but is not likely to adversely affect, listed or proposed threatened or endangered species or designated or proposed critical habitats in the action area:** Provide a letter from FWS concurring with the applicant's informal biological assessment. If any measures are proposed to mitigate any effects on species or habitats, the assessment must outline those measures with FWS concurrence.

_____ **If the proposed antenna structure may affect, and is likely to adversely affect, listed or proposed threatened or endangered species or listed or proposed designated critical habitats in the action area:** Prepare a formal biological assessment as outlined in 50 C.F.R. § 402.01 *et seq.* The applicant should provide the formal biological assessment to the Federal Communications Commission for formal consultation with the FWS.

_____ **(a)(4) may affect districts, sites, buildings, structures or objects significant in American history, architecture, archeology, engineering or culture, that are listed, or are eligible for listing, in the National Register of Historic Places**

_____ **For proposed facilities that would have no effect or no adverse effect on historic properties**, provide a letter from the relevant State Historic Preservation Officer (SHPO) to the applicant or its consultant regarding whether the proposed antenna structure may affect districts, sites, buildings, structures or objects, significant in American history, architecture, archeology, engineering or culture, that are listed, or are eligible, for listing, in the National Register of Historic Places (historic properties).

If you do not have a letter from the SHPO, provide documentation showing that the applicant complied with the Nationwide Programmatic Agreement for Review of Effects on Historic Properties for Certain Undertakings Approved by the Federal Communications Commission (NPA), 20 FCC Rcd 1073 (2004), *See* 47 C.F.R. §**1.1307(a)(4), Part 1 Appendix B.** *See also* http://wireless.fcc.gov/siting/npa.html.

If the proposed facility would come within an Exclusion under Section III of the NPA, provide a statement describing why the facility is excluded.

If the proposed facility would have no effect on historic properties, provide the date the Applicant filed its FCC Form 620 or FCC Form 621with the SHPO, showing that the 30-day period outlined in Section VII.B.2. of the NPA has expired.

If the proposed facility would have no adverse effect on historic properties, provide the date the Applicant filed its FCC Form 620 or FCC Form 621

[6] If available, provide information about post-high school formal education including degrees held, area(s) of expertise, years of experience, and membership in any relevant professional accreditation organizations.

with the SHPO, showing that the 30-day period outlined in Section VII of the NPA has expired. The Applicant should also document the date it submitted the FCC Form 620 or FCC Form 621 to the FCC for a 15-day review period (for material submitted electronically) or a 25-day review period (for material submitted by other means), pursuant to Section VII.C.2. of the NPA.

_____ **If the proposed facility would have an adverse effect on historic properties**, provide a copy of the Memorandum of Agreement (MOA) executed by the Applicant, the Federal Communications Commission, the SHPO, and the Advisory Council on Historic Preservation, if applicable, pursuant to Section VII. D.4. of the NPA.

_____ **For all proposed facilities**, in addition to the SHPO letter, other documentation of compliance with the NPA, or MOA, provide a copy of the Applicant's notification to potentially affected Indian tribes through the FCC Tower Construction Notification System (TCNS) or documentation of other reasonable and good faith efforts to identify and contact federally recognized Indian tribes and Native Hawaiian organizations, and a statement showing compliance with the procedures outlined in Clarification of Procedures for Participation of Federally-recognized Indian Tribes and Native Hawaiian Organizations Under the Nationwide Programmatic Agreement, *Declaratory Ruling,* FCC 05-176, released October 5, 2005. *See* http://wireless.fcc.gov/siting/.

_____ (a)(5) may affect Indian religious sites

Applicant provided insufficient information for the Commission's staff to determine whether the proposed facility satisfies § 1.1307(a)(5).

Provide an explanation of how the applicant determined that the proposed facility would not affect Indian religious sites. Provide documentation of the applicant's good faith efforts to determine whether the proposed antenna structure may affect any Indian religious sites, including any archeological effects on Indian burial mounds. Attach copies of any letters or studies completed by archeologists for the proposed antenna structure. Include reference to any databases, maps, or other sources consulted to identify Indian Tribes whose religious sites might be affected. Attach copies of all correspondence the applicant or its consultant sent to or received from an Indian Tribe regarding the proposed antenna structure, other than correspondence that the Tribe has asked to maintain confidential.

The FCC recognizes that Indian Tribes, as domestic dependent nations, exercise inherent sovereign powers over their members and territory. Applicants consulting with tribal authorities are acting as delegates of the FCC, which has a government-to-government relationship with tribes. Tribal authorities may request FCC participation in consultation on any matter at any time. Any information regarding historic properties or religious or sacred sites to which an Indian Tribe attributes significance may be highly confidential, private, and sensitive, and applicants should respect the wishes of the Tribe with respect to the treatment of such information.

_____ **(a)(6) will be located in a floodplain**

Applicant provided insufficient information for the Commission's staff to determine whether the proposed facility satisfies § 1.1307(a)(6).

If the proposed facility would not be located in a flood plain, provide a copy of the section of the relevant map from the Federal Emergency Management Agency (FEMA) showing that the proposed antenna structure will not be located in a flood plain.

If the proposed facility would be located in a flood plain, provide a copy of the section of the relevant map from the Federal Emergency Management Agency (FEMA) showing the location of the proposed antenna structure. In addition, provide a copy of the building permit from the local jurisdiction where the proposed antenna structure will be located that shows the proposed structure is at least one foot above the flood plain. If the local jurisdiction does not issue building permits, provide independent verification that shows the proposed structure is at least one foot above the flood plain.

_____ **(a)(7) construction will involve significant change in surface features (*e.g.*, wetland fill, deforestation or water diversion)**

Applicant provided insufficient information for the Commission's staff to determine whether the proposed facility satisfies § 1.1307(a)(7).

If the proposed facility would not be located in a wetland, provide a copy of the section of a map showing that the proposed antenna structure will not be located in a wetland.

If the proposed facility would be located in a wetland, provide a copy of the permit the applicant or its consultant received from the U.S. Army Corps of Engineers permitting the construction of the proposed antenna structure.

_____ **(a)(8) will be equipped with high intensity white lights which are to be located in residential neighborhoods, as defined by the applicable zoning law**

Applicant provided insufficient information for the Commission's staff to determine whether the proposed facility satisfies § 1.1307(a)(8).

Provide documentation that the proposed antenna structure will not be located in a residential neighborhood, as defined by the applicable zoning law (relevant only where high intensity white lights are required by the Federal Aviation Administration (FAA)).

_____ **(b) would cause human exposure to levels of radiofrequency radiation in excess of Commission-adopted guidelines**

Applicant provided insufficient information for the Commission's staff to determine whether the proposed facility satisfies § 1.1307(b).